MOTOR STARTER DISCONNECT AND CONTROLS

		MOTOR											STARTER										DISCONNECT MEANS											CONTROL			FEEDER				
		CHARACTERISTICS									LOCATION		TYPE					LOCATION					TYPE					LOCATION												
MARK	NAMEPLATE	HORSEPOWER (HP)	LOAD (kVA)	120V-1PH	208V-1PH	208V-3PH	240V-1PH	240V-3PH	277V-1PH	480V-1PH	480V-3PH	ROOM NUMBER	ROOM NAME	NEMA SIZE	MANUAL	MAGNETIC	BUILT-IN MOTOR O/L	2-SPEED	VFD	SEE NOTE	NEAR MOTOR	MOTOR CONT CENTER	EQUIP CONT PANEL	ROOM NUMBER	SEE NOTE	FURNISHED BY	DISC SWITCH	MANUAL STARTER	RECEPTACLE	FEEDER SW OR BREAKER	NEMA TYPE	DISC SIZE	FUSE SIZE	NEAR MOTOR	MOTOR CONT CENTER	EQUIP CONT PANEL	PANELBOARD	SEE NOTE	FURNISHED BY	INTERLOCK WITH MOTOR NO. BY E.C.	MANUAL AT STARTER	INTEGRAL WITH EQUIPMENT	FURNISHED BY	SEE NOTE	NUMBER OF CONDUCTORS	WIRE SIZE	GROUND SIZE	CONDUIT SIZE	SEE NOTE
			0																																													
3-AHU2	AH UNIT		1.248		•								MECH. RM. 106M													DIV 23	•							•					DIV 26				DIV 23		2	12	12	0.75	
3-CU1	OUTDOOR UNIT		27.957			•							OUTSIDE														•											DIV 26				DIV 23		3	2	8	1.25	
3-CU2	OUTDOOR UNIT		6.032		•								OUTSIDE														•											DIV 26				DIV 23		2	8	10	0.75	
3-EF1	EXHAUST FAN		0.4	•									WAITING	0	•									100A	DIV 26	•							•					DIV 23				DIV 23		2	12	12	0.75	
3-RF1	RETURN FAN	1.5	2.12			•							ROOF						•					100A	DIV 26	•							•					DIV 26				DIV 23		3	12	12	0.75	
3-SF1	SUPPLY FAN	7.5	8.7			•							MECH. RM.						•		•				DIV 26	•							•					DIV 26				DIV 23		3	8	10	0.75	

Panel: 3-1S-3

Location: Elec. 100A
Supply From:
Voltage: 120/208 Wye-3PH-4W

Mounting: Surface
Enclosure: Type 1

A.I.C. Rating:
Mains Type: M.B.
Mains Rating: 225 A

CKT	Circuit Description	Trip	Poles	A	B	C	Poles	Trip	Circuit Description	CKT
1	Lighting	20 A	1	768 VA	768 VA		1	20 A	Lighting	2
3	Lighting	20 A	1		640 VA	512 VA	1	20 A	Lighting	4
5	Receptacle	20 A	1			900 VA	672 VA	1	20 A	Lighting	6
7	Receptacle	20 A	1	900 VA	1080		1	20 A	Receptacle	8
9	Receptacle	20 A	1		900 VA	900 VA	1	20 A	Receptacle	10
11	Receptacle	20 A	1			900 VA	900 VA	1	20 A	Receptacle	12
13	Receptacle	20 A	1	900 VA	900 VA		1	20 A	Receptacle	14
15	Receptacle	20 A	1		900 VA	900 VA	1	20 A	Receptacle	16
17	Receptacle	20 A	1			900 VA	900 VA	1	20 A	Receptacle	18
19	Receptacle	20 A	1	900 VA	900 VA		1	20 A	Receptacle	20
21	Receptacle	20 A	1		720 VA	900 VA	1	20 A	Receptacle	22
23	Receptacle	20 A	1			900 VA	900 VA	1	20 A	Receptacle	24
25	Receptacle	20 A	1	900 VA	500 VA		1	20 A	Receptacle	26
27	Receptacle	20 A	1		1180	540 VA	1	20 A	Receptacle	28
29	3-CU1	100	3			9319 2900	3	40 A	3-SF1	30
31	--	--	--	9319	2900		--	--	--	32
33	--	--	--			9319 2900	--	--	--	34
35	3-EF1	20 A	1			400 VA 707 VA	3	20 A	3-RF1	36
37	Control PNL	20 A	1	180 VA	707 VA		--	--	--	38
39	AH Rec/Lts	20 A	1			180 VA 707 VA	--	--	--	40
41	Spare	20 A	1			0 VA 0 VA	1	20 A	Spare	42
43	Spare	20 A	1	0 VA	0 VA		1	20 A	Spare	44
45	Spare	20 A	1			0 VA 0 VA	1	20 A	Spare	46
47	Space	--	--			0 VA 0 VA	--	--	Space	48
49	Space	--	--	0 VA	0 VA		--	--	Space	50
51	Space	--	--			0 VA 0 VA	--	--	Space	52
53	Space	--	--			0 VA 0 VA	--	--	Space	54
	Total Load:			21.62 kVA		20.30 kVA				

Notes: REFER TO SINGLE LINE FOR FAULT CURRENT RATING.

TOTAL CONNECTED		ESTIMATED DEMAND
63.12 kVA		54 KVAD (150A)

Panel: 3-1N-3a

Location: Mech. Rm. 106M
Supply From:
Voltage: 120/208 Wye-3PH-4W

Mounting: Surface
Enclosure: Type 1

A.I.C. Rating:
Mains Type: M.L.O.
Mains Rating: 60 A

CKT	Circuit Description	Trip	Poles	A	B	C	Poles	Trip	Circuit Description	CKT
1	3-AHU2	15 A	2	624 VA	3016		2	50 A	3-CU2	2
3	--	--	--		624 VA	3016	--	--	--	4
5	Spare	20 A	1			0 VA 0 VA	1	20 A	Spare	6
7	Spare	20 A	1	0 VA	0 VA		1	20 A	Spare	8
9	Spare	20 A	1		0 VA	0 VA	1	20 A	Spare	10
11	Spare	20 A	1			0 VA 0 VA	1	20 A	Spare	12
13	Spare	20 A	1	0 VA	0 VA		1	20 A	Spare	14
15	Spare	20 A	1		0 VA	0 VA	1	20 A	Spare	16
17	Space	--	--			0 VA 0 VA	--	--	Space	18
19	Space	--	--	0 VA	0 VA		--	--	Space	20
21	Space	--	--		0 VA	0 VA	--	--	Space	22
23	Space	--	--			0 VA 0 VA	--	--	Space	24
25	Space	--	--	0 VA	0 VA		--	--	Space	26
27	Space	--	--		0 VA	0 VA	--	--	Space	28
29	Space	--	--			0 VA 0 VA	--	--	Space	30
	Total Load:			3.64 kVA	3.64 kVA	0.00 kVA				

Notes: REFER TO SINGLE LINE FOR FAULT CURRENT RATINGS.

TOTAL CONNECTED		ESTIMATED DEMAND
7.28 kVA		6.2 KVAD (17A)

GENERAL NOTES

A DARK LINEWEIGHT INDICATES NEW WORK, LIGHT DASHED LINEWEIGHT INDICATES FUTURE PHASE WORK, LIGHT LINEWEIGHT INDICATES EXISTING WORK.

NOTES

1 INTERCEPT AND EXTEND 4-4/0 AWG, #4 GRD, IN 2.5"C. AS REQUIRED FOR NEW PANEL LOCATION.

2 EXISTING SURFACE MOUNTED PANEL TO BE REMOVED AND REPLACED WITH NEW. REFER TO FLOOR PLAN FOR ADDITIONAL DETAILS.

3 UTILIZE EXISTING SPARE(OFF) 60A/3P BREAKER IN EXISTING PANEL "3-1N-3" FOR NEW WORK.

4 RUN 4-#6, #10 GRD. IN 1"C.

PMT 3
4160-208Y/120V
150 KVA
1.5%
(27,790 SCA)



SINGLE LINE DIAGRAM

NO SCALE

A 3E601

FULLY SPRINKLERED

Revisions		Date
1	ADDENDUM 2	3/13/14

CONSULTANTS:

Heapy Engineering
Mechanical Electrical Commissioning Technology
Nationally Recognized Leader in Sustainability / LEED
1400 W Dorothy Lane, Dayton OH 45409-1310
Ph: 937-224-0861 Fax: 937-224-5777 www.heapy.com
Heapy Project No. 2011-04033 Firm License No. 01528

STATE OF OHIO · JOHN A. BLACK · 49341 · REGISTERED PROFESSIONAL ENGINEER

ARCHITECT/ENGINEERS:

JOHN POE ARCHITECTS
116 EAST THIRD STREET
DAYTON, OHIO 45402-2130
937 461 3290 PHONE
937 461 0260 FAX
joa@johnpoe.com

Drawing Title: SCHEDULES AND DETAILS

Approved: Project Director

Project Title: Renovate Occupational Therapy Building 3

Location: Chillicothe, Ohio

Date: 02/04/2013 | Checked: MSG | Drawn: JAS

Project No. VA Project No. 538-13-101 JPA Project No. 11013.00

Building Number: 3

Drawing Number: 3E601

Dwg. of xx

Office of Construction and Facilities Management
Department of Veterans Affairs

EXISTING PANEL 3-1N-3
C 3EP101 **SITE PHOTOGRAPHS**

GENERAL NOTES

A. PROVIDE DEDICATED NEUTRAL FOR ALL 120V-20A CIRCUITS.
B. PROVIDE PRINTED LABELS ON ALL RECEPTACLE AND SWITCH COVERPLATES INDICATING PANEL AND CIRCUIT NUMBER.
C. EMT CONDUIT SHALL BE 0.75" MINIMUM.
D. REFER TO DIVISION 22/ARCHITECTURAL DRAWINGS FOR LOCATIONS OF ALL PLUMBING EQUIPMENT.
E. CONTRACTOR SHALL INSTALL ELECTRICAL CONDUIT/FEEDERS TIGHT TO STRUCTURE TO ALLOW FOR REQUIRED CLEARANCES AROUND OTHER TRADES ABOVE CEILING EQUIPMENT.
F. (1) EACH BRANCH CIRCUIT HOMERUN SHALL HAVE NO MORE THAN THREE CIRCUITS. EACH BRANCH CIRCUIT SHALL HAVE A SEPARATE NEUTRAL AND GREEN INSULATED EQUIPMENT GROUNDING CONDUCTOR.
G. MULTI-GANG BACKBOXES FOR DIFFERENT VOLTAGES AND TYPES OF EMERGENCY AND NORMAL BRANCH WIRING DEVICES SHALL HAVE DIVIDERS BETWEEN DEVICES.
H. INCLUDE ALL WORK NECESSARY TO ACCOMMODATE PHASING.
I. REFER TO ARCHITECTURAL DRAWINGS AND GENERAL REQUIREMENTS SECTION 01 00 00.
J. REFER TO ARCHITECTURAL DRAWINGS FOR RATED WALL LOCATIONS.
K. REFER TO ARCHITECTURAL ELEVATIONS FOR EXACT LOCATIONS OF DEVICES MOUNTED ABOVE OR BELOW CASEWORK, FURNITURE, LAVATORIES, ETC.

NOTES

1. EXISTING MANUFACTURING EQUIPMENT (BASEBALL CARD SORTING MACHINE) TO BE REMOVED FROM BUILDING 25 AND RELOCATED TO BUILDING 3 BY VA. PROVIDE 60A/3P DISCONNECT. RUN 3-#6, #10 GRD. IN 1.25"C. PROVIDE NEW 40A/3P BREAKER IN EXISTING WESTING HOUSE PANEL (UTILIZE SPACE CREATED FROM REMOVAL WORK) FOR NEW WORK. VERIFY EXACT LOCATION WITH COTR PRIOR TO ROUGH-IN.
2. EXISTING MANUFACTURING EQUIPMENT (BASEBALL CARD SHRINK WRAP MACHINE) TO BE REMOVED FROM BUILDING 25 AND RELOCATED TO BUILDING 3 BY VA. PROVIDE 30A/3P DISCONNECT. RUN 3-#10, #10 GRD. IN 0.75"C. PROVIDE NEW 30A/3P BREAKER IN EXISTING WESTINGHOUSE PANEL (UTILIZE SPACE CREATED FROM REMOVAL WORK) FOR NEW WORK. VERIFY EXACT LOCATION WITH COTR PRIOR TO ROUGH-IN.
3. NEW SURFACE MOUNTED PANEL. UTILIZE EXISTING FEEDER FOR NEW WORK. REFER TO SINGLE LINE FOR ADDITIONAL DETAILS.
4. SAW CUT EXISTING FLOOR SLAB TO ACCOMMODATE NEW FLOOR BOX AND CONDUIT. PATCH AND REPAIR EXISTING SLAB TO ENSURE A PROPER / CLEAN INSTALLATION.
5. PROVIDE NON-METALLIC FLOOR BOX MADE OF HIGH-STRENGTH RIGID PVC CONSTRUCTION (NON-CORROSIVE). BOX MUST HAVE OVERSIZED 1.5" (DATA) AND 1" (POWER) CONDUIT HUB. MINIMUM DEPTH OF POUR SHALL NOT EXCEED 3". PROVIDE FLOOR BOX WITH UNIVERSAL CARPET FLANGE (MADE OF CAST ALUMINUM) AND COVER ASSEMBLY. PROVIDE WITH (4) 20A, 125V RECEPTACLES AND (4) KEYSTONE OPENINGS FOR DATA JACKS OR FLUSH A/V CONNECTORS. VERIFY COLOR FINISH WITH ARCHITECT / COTR.
6. INTERCEPT AND EXTEND EXISTING CIRCUITS TO REMIAN TO NEW PANEL "3-1S-3. INCLUDE 10-120V-20A/1P CIRCUITS IN BID FOR WORK.
7. LOW VOLTAGE TRANSFORMER FOR SENSOR OPERATED FLUSH VALVES PROVIDED BY DIVISION 22.
8. PROVIDE RECESSED 4" SQ J-BOX AND 0.75"C. TO ABOVE ACCESSIBLE CEILING FOR LOW VOLTAGE WIRING BY DIVISION 22. COVER PLATE BY DIVISION 22. COORDINATE EXACT M.H. WITH DIVISION 22. PRIOR TO ROUGH-IN.
9. LOW VOLTAGE TRANSFORMER ABOVE LAY-IN CEILING FOR SENSOR OPERATED FAUCET PROVIDED BY DIVISION 22.
10. PROVIDE RECESSED SINGLE GANG J-BOX AND 0.75"C. TO ABOVE ACCESSIBLE CEILING FOR LOW VOLTAGE WIRING BY DIVISION 22. PROVIDE GROMMETTED OPENING. COORDINATE EXACT M.H. WITH DIVISION 22 PRIOR TO ROUGH-IN.
11. EXISTING AREA TO REMAIN UNCHANGED UNLESS OTHER WISE NOTED.
12. UTILIZE EXISTING 20A/1P BREAKER CREATED FROM REMOVAL FOR NEW WORK.
13. WIRE THRU STARTER LOCATED IN ELECTRIC ROOM.
14. WIRE THRU VFD LOCATED IN ELECTRICAL ROOM.
15. EXISTING AREA SHALL BE RENOVATED BY VA. NO WORK OTHER THAN WHAT IS INDICATED IS REQUIRED WITHIN THIS SPACE.
16. EXISTING MAIN ELECTRIC ROOM IS LOCATED BELOW (WITHIN PIPE BASEMENT).
17. CONNECT TO LOCAL 120V NORMAL POWER RECEPTACLE CIRCUIT PRESENTLY SERVING THIS AREA.
18. PROVIDE NEW 208V-30A/3P DISCONNECT SWITCH WITH "SWITCH OPEN" AUXILIARY CONTACTS. WIRE TO VFD IN ELECTRIC ROOM TO SHUTDOWN UPON OPENING OF DISCONNECT SWITCH.



EXISTING PANELS 3-1S-1 & 2
B 3EP101 **SITE PHOTOGRAPHS**

RELOCATED PACKAGING EQUIPMENT
A 3EP101 **SITE PHOTOGRAPHS**

N 1 FLOOR PLAN - POWER
Scale: 1/8" = 1'-0"

FULLY SPRINKLERED

Revisions		Date
1	ADDENDUM 2	3/13/14

CONSULTANTS:

Heapy Engineering
Mechanical Electrical Commissioning Technology
Nationally Recognized Leader in Sustainability / LEED
1400 W Dorothy Lane, Dayton OH 45409-1310
Ph: 937-224-0861 Fax: 937-224-5777 www.heapy.com
Heapy Project No. 2011-04033 Firm License No. 01528

STATE OF OHIO — JOHN A. BLACK 49341 — REGISTERED PROFESSIONAL ENGINEER

ARCHITECT/ENGINEERS:

JOHN POE ARCHITECTS
116 EAST THIRD STREET
DAYTON, OHIO 45402-2130
937 461 3290 PHONE
937 461 0260 FAX
jpa@johnpoe.com

Drawing Title: FLOOR PLAN - POWER

Approved: Project Director

Project Title: Renovate Occupational Therapy Building 3

Location: Chillicothe, Ohio

Date: 02/04/2013 | Checked: MSG | Drawn: JAS

Project No. VA Project No. 538-13-101 JPA Project No. 11013.00

Building Number: 3

Drawing Number: 3EP101 Dwg. of xx

Office of Construction and Facilities Management
Department of Veterans Affairs